

Fan Control Using AgSense Field Commander

Only use these instructions where the existing fan controls are 120v AC using the simple start and stop buttons as shown in the picture below.

Wiring instructions – see picture below:

1. Connect the Black wire from the Field Commander to the fused 120v source.
2. Connect the Brown/Black Stripe wire to the Neutral terminal on the 120v transformer.
3. Locate the 120v wire that connects the stop button to the contactor coil. Cut or disconnect this wire and connect our Red wire to the wire that goes back to the stop button, and connect our Red/Black Stripe wire to the wire that goes to the contactor coil. See attached picture below.

EXISTING CONTROLS

